

Quick Start for Windows Me/NT/2000/98

This quick start guide covers the standard installation on the PC running Windows NT/2000/98. See the PowerRIP 2000 User's Guide for detailed information.

Before you install PowerRIP 2000:

Set up your printer according to your printer documentation.

Follow these steps as you set up and print from PowerRIP 2000:

- A. Install the PowerRIP 2000 software
- B. Validate PowerRIP 2000
- C. Test PowerRIP 2000

A. Install the PowerRIP 2000 software

1. Insert the PowerRIP 2000 CD into your CD-ROM drive. The PowerRIP 2000 splash screen will display.
2. Click on Install PowerRIP 2000. The Choose Setup Language dialog will display. Select the language you wish to install. Click OK. The Setup dialog will display momentarily and then the Select Location dialog will display. Select the default page size you wish to install. Click Continue.
3. The Please Select Version dialog will display. Select the version of PowerRIP 2000 you wish to install. Click Continue.
4. The Welcome screen will display. Click Next.
5. The Software License Agreement will display. Click Yes.
6. The Select Components dialog will display. Select the component for your printer. Click Next.
7. The Select Program Folder dialog will display. Click Next. The PowerRIP 2000 program will start installing on your hard drive.
8. The PowerRIP 2000 Print Manager Setup dialog will display. The printer component you selected in Step 6 should highlight the appropriate printer in this window. If it doesn't, select your printer.

Note: Windows NT 4.0 only – It will ask you what port. Select PowerRIP port.

9. The Setup Complete dialog will display. Click Finish. Your computer will restart.

B. Validate PowerRIP 2000

When you register your PowerRIP 2000 on the internet you create an account of five validations that you can access 24 hours a day. The first time you validate your PowerRIP 2000 you will use one of your five validations. You will then have four validations left in your account. Remove and Restore validation only when moving PowerRIP 2000 to another computer or when upgrading the operating system. The number of times you may restore and use validation is unlimited.

Note: If PowerRIP 2000 is not validated, “PowerRIP” will print across the page.

1. Launch PowerRIP 2000. (Start>Programs>PowerRIP 2000 OKI>PowerRIP 2000 OKI.
2. Maximize PowerRIP 2000. Go to File>Install PowerRIP Validation. The PowerRIP 2000 validation dialog will display. You will find your User Code in this dialog.
3. Go to the iProof Systems internet site
<http://www.iproofsystems.com>
Go to Product Registration.
Fill out the registration information and click Submit. In the next menu click Validate PowerRIP 2000.
4. Type your Product Code and User Code and click Submit. Your Validation code will display.
5. Type the Validation code in the PowerRIP 2000 Install Validation dialog in the Activation Code space. Click OK. You will get the message Validation complete.
6. Restart your PowerRIP 2000. Click OK. Your PowerRIP 2000 is validated.

C. Test PowerRIP 2000

1. Launch PowerRIP 2000 (See Step 1 Section B for launch sequence).
2. Maximize PowerRIP 2000. Go to File>Print PostScript File. The Open dialog will display. You should be in the PRPC2000 OKI folder
3. Highlight Train and click Open.
4. The Configure Document Specs window will display. Make sure the correct printer and LPT port is selected.
5. Select paper and resolution. Click OK. The file will process and print.

Print the PowerRIP 2000 Manual

1. Launch PowerRIP 2000.
2. Go to File>Print PostScript File.
3. Change File Type to “All Files.”
4. In “Look in” go to the PowerRIP 2000 folder on your hard drive.
Open the DOCS folder. Open the appropriate folder for your country.
6. Highlight PC Manual.PDF. Click Open
7. In the “Configure Document Specs” dialog make sure your printer and port are correct.
8. Select “Use Document Default Settings.”
9. Click OK. Your manual will print.

Where to Get Help

Your PowerRIP 2000 folder on your hard drive contains helpful ReadMe PDFs that will guide you through printing from popular applications, give you answers to frequently asked questions, and identify PostScript and System errors you may encounter. Also check our website's FAQ's Technical page.

iProof Systems Technical Support is available through phone, fax, mail, e-mail and the Internet. Telephone support hours of operation are 9:00 am to 6:00 pm EST (Monday through Friday). Free telephone support is limited to 30 days from your first support call.

After 30 days from your first call, a charge of \$25.00 (U.S. Dollars) applies per incident (billed to your credit card). Visa, MasterCard, and American Express are accepted.

Telephone Support

When calling for technical assistance, be ready to identify your system and its configuration, the Product Code of PowerRIP 2000, and a description of the problems you are encountering. It is highly recommended that you enable the Log Messages option when creating a PowerRIP 2000 printer. The entries in the log will help the support staff identify PostScript error messages .

Telephone: 321-751-2445 Fax: 321-751-2449

We suggest using iProof's free e-mail support to get a prompt answer to any questions you may have.

iProof Systems E-Mail Support

You can e-mail iProof Systems at Support@iproofsystems.com. Please include your name, PowerRIP 2000 Product Code, platform, printer model, along with a description of the problem you are encountering, so that a technical support representative can e-mail a response to your question.

World Wide Web

<http://www.iproofsystems.com>

Download PowerRIP 2000 updates from iProof Systems' website. On our home page, click Support to check if there is an update for your printer model.